



Butyl Products Ltd

11 Radford Crescent,
Billericay, Essex, CM12 0DW England.
Tel: 44 (0)1277 653281 **Fax:** 44 (0)1277 657921
E-mail: enquiries@butylproducts.co.uk.

Instructions for a Pipe Sleeve Kit

The kit consists of:-

- 1 x Fipec cold bonding tape.
- 1 x Jubilee clip
- 1 x Butyl pipe sleeve complete with flange
- 1 x Neoprene sponge strip.

Step 1 Cut a circle in the liner around the circumference of the pipe, leaving approximately a 1" clearance.

Step 2 Place the pipe sleeve over the pipe and offer the flange up to the liner, mark around the flange with a crayon.

Step 3 Ensure that the liner is clean within crayon border (a mild solvent such as Acetone or Toluene used sparingly with a cloth is suitable for cleaning material). Apply Fipec cold bonding tape around the inside edge of crayon border.

Step 4 Remove backing paper from Fipec bonding tape. Place the pipe sleeve over the pipe and press the flange firmly into Fipec cold bonding tape all around the edge.

Using a roller apply pressure all the way around to expel air and create a good bond.

Step 5 Remove backing paper from Neoprene sponge strip and stick around the circumference of the pipe.

Step 6 Tighten the jubilee clip and pipe sleeve where Neoprene sponge strip is located.



Website: www.butylproducts.co.uk
Directors: R.A. Young J.R. Young R.J. Martin J. Gander
Registered Office: 11 Radford Crescent, Billericay, Essex, CM12 0DW. Registration No.: GB 3141465